



ZENITH

The Zenith wireless system is designed for wireless ENG and HD live productions where range and signal reliability are essential. The unique network capability of the system allows for an almost infinite shooting area by deploying inexpensive receiver nodes wired with Category-5 cabling.

The bandwidth is adjustable (between 5-40MHz) and one of the strengths of the Zenith system is its ability to navigate around interference when operating in "wide-bandwidth mode" making the link robust and extremely stable.

Zenith is fully configurable via a Web interface and statistics can be monitored on portable devices (such as an iPhone©) allowing the operator the flexibility to configure the system for optimal HD wireless transmission within any environment.

Zenith provides a scalable modular solution allowing trade offs between budget and performance.

Features

- 80 milliseconds latency
- 5.1 - 5.9GHz license-exempt band (approx. 20 x 10MHz channels available)
- Range from camera back transmitter up to 1km
- Range (point-to-point) up to 10km
- 2 - 60Mb encoding bitrate
- Configure and monitor statistics via web page using a laptop, iPad©, iPhone©, or other popular portable device
- Secure encrypted transmission
- LED signal strength meter on transmitter and receiver

Specifications

Latency:	80 milliseconds
Compression:	H.264
Format:	SDI, HD-SDI, Composite up to 1080p 60
Audio Output:	2 channels embedded or balanced analogue line level
RF Power Output:	Up to 600mW adjustable
Modulation:	OFDM
Bandwidth:	5 - 40MHz
Frequency:	5.1 - 5.9GHz (approx. 30 channels)
Security:	256 bit encryption AES
Firmware:	Upgradable via Web page
Antennas:	2 way diversity and MIMO 3x3
Antenna Port:	N-Type
Range:	Up to 1km (camera back transmitter) Up to 10km (point-to-point)
Temperature Range:	-5° to 50° C
Made In:	United Kingdom



E&OE: Details subject to change. Photos for illustration purposes only.

Revolutionise the way you work

UK Head Office +44 (0)845 643 2874 • www.boxx.tv • sales@boxx.tv